

# RTS DV-2 SERIES KEY PAD FUNCTION - SOFTWARE 2.06

**Microphone must be set to the following settings:**  
Lock must be OFF - Only switch ON when you need to disable the keypad functions

**DTMF must always be set to the OFF position**

**Never set the DTMF ON = Keypad will not operate normally**



## 1) MICROPHONE KEYPAD:

- Use microphone keypad to change channels quickly. Example to go to channel Ch5= Press 0 0 5 on the keypad; Ch14= 0 1 4. Our radio channel capacity is 255 that is why you need to enter three digits on the keypad to change to the desire channel. You can also use the two button on top of the microphone to up/down the channels.
- Enable/disable radio scanning by pressing the “V/M” key on the microphone keypad

## 2) FRONT PANEL BUTTONS ON RADIO:

- SCAN ON/OFF = by pressing the V/M button
- Scan list editing – select the channel that you would like to edit. Press “FUNC” key then “SQ/C” key – the display it will indicate “SCAN ADD” this indication it that this channel will be scanned or “SCAN DEL” indicating that this channel is now removed from the scan list.
- Squelch editing – By pressing and hold the “SQ/C” button in and by using the “VOLUME CONTROL” turning it right or left will adjust the squelch setting = correct setting is “04”. The higher the number the stronger the signal the radio have be to receive. **Beware - Do not to set the Squelch to a HIGH level, by doing this you will decrease your communication range**
- Emergency – Press and hold the “ENTER” button for longer as 2 seconds. NB emergency function must be enabled on radio for this function to work properly.

## 3) CALL BUTTON – Front Panel & Microphone Keypad:

- This button only works when radio is set to operate with selective calling, 5 Tone. Call button = 5 Tone address book

**Please NOTE: These function can differ - Please consult your local dealer/installer**

086 100 2525  
info@rtsradio.co.za  
www.rtsradio.co.za

**RTS** 